



# MT65 Beluga Lite

Terminale mobilne

|   |  |  |  |  |   |
|---|--|--|--|--|---|
| <br>1.2m drop        | <br>1D & 2D       | <br>3,800 mAh | <br>4.0" screen | <br>4G          | <br>Acuscan          |
| <br>Android 8.1      | <br>Bluetooth 4.2 | <br>Camera    | <br>GMS         | <br>GPS         | <br>IP65             |
| <br>LED aimer        | <br>Micro SD      | <br>Micro USB | <br>Ndevor      | <br>Touchscreen | <br>Warranty 2 Years |
| <br>WiFi Dual Band |  |  |  |  |   |



## Features

### Android 8.1

The Android 8.1 OS of the MT65 Beluga Lite ensures near endless application possibilities. It gives you the data security and admin tools you need for control and complete peace-of-mind.

### VGA barcode scanner.

With its 2D VGA barcode reader, the MT65 Beluga Lite provides an excellent scanning performance and scans almost any 1D and 2D barcode with impressive speed and ease.

### Versatile data input.

The MT65 Beluga Lite Mobile Computer combines a touch screen with a physical keyboard. The touchscreen allows you to easily navigate through applications while the keypad can be used for quick and easy stock quantities input.

### Long-lasting battery.

The MT65 Beluga Lite provides up to 10 hours of battery life, so rest assured it will last a full shift. Does your application require a longer duration? A replaceable battery and charging cradle with an extra battery slot got you covered. You can easily switch the battery and quickly proceed with scanning.

### Angled scanning for increased comfortability.

The megapixel scan engine on the MT65 Beluga Lite is set at an angle. This means that the screen and keypad remain visible to the operator, even when scanning codes above shoulder height.

### GMS-certified.

The MT65 Beluga Lite comes with an Android 8.1 GMS-certified operating system. Google Mobile Services (GMS) offers integrated Google applications such as Gmail, Google Maps, and Google Play Store.

### Accessories to cover all your needs.

You can choose between various additional accessories for the MT65 Beluga Lite: a single slot charging and communication (USB) cradle, pistol grip, multi-charger, and holster.

TECHNICAL SPECIFICATIONS  
**MT65 Beluga Lite**

**Przechwytywanie danych**

|                |                             |
|----------------|-----------------------------|
| 1D             | All major 1D symbologies    |
| 2D             | All major 2D symbologies    |
| Celowanie      | LED                         |
| Oświetlenie    | Biała dioda LED (625±10 nm) |
| Czujnik obrazu | 640 x 480 CMOS              |

**Wydajność**

|                              |                            |
|------------------------------|----------------------------|
| Obecny system operacyjny     | Android 8.1, GMS           |
| Pamięć Flash                 | 16GB                       |
| Pamięć RAM                   | 2GB                        |
| Rozszerzenie pamięci (maks.) | Micro SD card (max. 128GB) |
| Procesor                     | 1.5 GHz quad-core          |

**Właściwości fizyczne**

|                              |  |
|------------------------------|--|
| Typ Baterii                  | 3.7 V, 3800 mAh                            |
| Wymiary (mm)                 | 166(W) x 73(D) x 26(H) mm                  |
| Wyświetlacz                  | 4" WVGA (800 x 480)                        |
| Gniazdo rozszerzeń           | Micro SD card (max. 128GB)                 |
| Oczekiwana żywotność baterii | 10 hours                                   |
| Oczekiwany czas ładowania    | 4.5-5 hours (charge via AC adapter)        |
| Interfejsy                   | Micro USB 2.0                              |
| Klawiatura                   | 30 klawiszy                                |
| Powiadomienia                | Głośnik, Wibracja, Wielokolorowe diody LED |
| Zasilanie wejściowe          | AC 100 to 240 V (50 to 60 Hz)              |
| Zasilanie wyjściowe          | DC5 V, 2.0 A                               |
| Tylny aparat                 | Lampa błyskowa LED, Autofokus, 8 MP        |
| Panel dotykowy               | Ekran dotykowy pojemnościowy               |
| Waga                         | 330 g (including battery)                  |

**Bezprzewodowy**

|            |  |
|------------|--|
| GPS        | GLONASS, GPS (AGPS)  |
| WLAN RADIO | IEEE 802.11 a/b/g/n, 2.4GHz and 5GHz                                       |
| WPAN RADIO | Bluetooth 4.2 LE, backward compatible                                      |
| WWAN RADIO | TD-LTE (B38, B39, B40, B41) FDD-LTE (B1, B2, B3, B5, B7, B8, B20, B28 a&b) |

**Środowiskowe**

|                                    |  |
|------------------------------------|--|
| Odporność na upadek                | 1.2 m  |
| Wyładowanie elektrostatyczne (ESD) | ±8 kV (wyładowanie bezpośrednie), ±15 kV (wyładowanie w powietrzu) |
| Wilgotność                         | 5% do 95% (bez kondensacji)  |
| Klasa IP                           | IP65   |

|                     |                                     |
|---------------------|-------------------------------------|
| Temperatura robocza | od -20°C do 50°C (od -4°F do 122°F) |
|---------------------|-------------------------------------|

|                            |                                      |
|----------------------------|--------------------------------------|
| Temperatura przechowywania | od -30°C do 70°C (od -22°F do 158°F) |
|----------------------------|--------------------------------------|

#### Oprogramowanie

|                          |        |
|--------------------------|--------|
| Narzędzia konfiguracyjne | Ndevor |
|--------------------------|--------|

|                     |                        |
|---------------------|------------------------|
| MDM (certyfikowany) | Ndevor, SOTI, Airwatch |
|---------------------|------------------------|

|                    |                             |
|--------------------|-----------------------------|
| Emulacja terminala | StayLinked, Ivanti Velocity |
|--------------------|-----------------------------|

#### Certyfikaty

|                    |                                   |
|--------------------|-----------------------------------|
| Certyfikaty Sprzęt | FCC ID, IEC 62471, RoHS, EN 60950 |
|--------------------|-----------------------------------|

#### Gwarancja

|                       |        |
|-----------------------|--------|
| Standardowa gwarancja | 2 lata |
|-----------------------|--------|

#### Akcesoria

|                      |   |
|----------------------|---|
| Akcesoria opcjonalne | Kabel USB, 4-gniazdowa ładowarka akumulatorów, Podstawa ładująca, Uchwyt pistoletowy, Bateria, Adapter, Szybka ochronna |
|----------------------|---|

|                       |  |
|-----------------------|--|
| Akcesoria standardowe | Kabel USB, Pasek na rękę, Bateria, Zasilacz sieciowy |
|-----------------------|--|

#### Newland AIDC EMEA

Feel free to contact us or a partner near you.

[info@newland-id.com](mailto:info@newland-id.com) - [newland-id.com](http://newland-id.com)

Specifications are subject to change without notice

© Newland AIDC EMEA 2026 - All rights reserved